



**±48V DC Input Industrial PC PS2 4U ATX  
Switching Mode Hot Swap  
Mini Redundant Power Supply**

Series	Model No.	Output Watts	Input Voltage	Input Voltage range	Polarity reverse protection
<b>48</b>	STC-48600RD	600 W continuous	±48V DC	±36V ~ ±72V DC	<b>By fuse</b>

**ENVIRONMENTAL CONDITIONS:**

- ▶ Cooling: Forced Air-cooling, **40x40x28 mm Fan x 2 (With Two Ball Bearing)**
- ▶ Fan brand: DELTA, NMB, SUNON, SUNON IP68 (for H version). Specifications are equivalent
- ▶ Operating Temperature: **0°C~+50°C (Full Load)**
- ▶ Output Power: 100% @ 50°C, 70% @ 60°C
- ▶ Operating Humidity: 20%~85% RH. (No condensing) **(95% Optional)**
- ▶ Storage Temperature: -20°C~+80°C
- ▶ Storage Humidity: 10%~90% RH. (No condensing)
- ▶ Operating Altitude: 10M Below Sea level to 3000M Above Sea level

**DC INPUT CHARACTERISTICS:**

- ▶ Input connector type 30A/300V UL Approved Gold Plated Brass 1.2f/2 Terminal
- ▶ Input Current 10.4A/20.8A(600W) @ Full Load High Line & Low Line
- ▶ Inrush Current Less than 50A Cold start @ 25°C ambient

**DC OUTPUT CHARACTERISTICS:**

Output Voltage	Regulation			Output Current		Ripple & Noise
	Load	Line	Cross	<b>600W</b>		
				Min.	Max.	
<b>+5V</b>	±5%	±1%	±5%	1A	35A	50mV
<b>+12V</b>				1A	40A	120mV
<b>+3.3V</b>				0.5A	25A	50mV
<b>-12V</b>	±8%			0A	1A	120mV
<b>-5V (Optional)</b>	±5%			0A	0.5A	50mV
<b>+5VSB</b>	±5%			0A	3.5A	50mV
Maximum continuous combined load on +3.3 V & +5V DC output shall not exceed				<b>175</b>		<b>Wattage</b>
Maximum continuous combined load on +3.3 V & +5V and 12V DC output shall not exceed				<b>570</b>		
Maximum continuous total DC output power shall not exceed				<b>500</b>		

**OVERALL PERFORMANCE:**

- ▶ Efficiency: **82% typical @ 48V DC Full Load**
- ▶ Hold up time: When power shut down DC output 5V must be maintain 1ms @48V DC
- ▶ Rise time:

- ▶ Power Good Signal: TTL Compatible signal, on delay 100~500ms, off delay 1ms min.
- ▶ Short Circuit Protection (SCP): All output equipped with SCP (shutdown and latch off)
- ▶ Over Power Protection (OPP): Peak power protected to 130±10% of continuous rated power (shutdown and latch off)
- ▶ Over Voltage Protection (OVP): +3.3V @3.6V~4.3V DC, +5V @5.5V~6.5V DC, +12V @13.2~15.6V DC

#### **RELIABILITY:**

- ▶ MTBF: 100,000 hours @ Max. Load, 48V DC & 25°C ambient
- ▶ Safety Standards: Meet IEC60950-1, TÜV EN60950-1
- ▶ Safety Approved:
- ▶ EMI Compatibility (EMC): EN55032:2015/AC:2016, CISPR32:2015, EN61000-3-2:2014, EN61000-3-3:2013, EN55024:2010 +A1:2015

#### **ISOLATION:**

- ▶ INPUT and OUTPUT are isolated by transformers and optical couplers
- ▶ Dielectric Withstand: INPUT to OUTPUT: 1000V DC for 60 seconds
- ▶ Dielectric Withstand: INPUT to FRAME GROUND: 1000V DC for 60seconds
- ▶ Leakage Current: <0.005µA @ 48V DC

#### **LED indicator:**

Power module 1 Green LED when power on  
Power module 2 Green LED when power on

#### **Alarm function:**

In the rear panel with power failure alarm signal to indicate when power failure wire.

#### **Alarm reset switch**

To reset by switch

#### **Output Device Connector Specific:**

ATX 24 Pins x 1	Molex 29-01-2240 or equivalent
+12V(P4) 4 Pins x 1	Molex 39-01-2040 or equivalent
HDD, DVD 4 Pins x 4	Molex 8981-04P or equivalent
FDD 4 Pins x 1	AMP 171822-4 or equivalent
Serial ATA x 2	Molex 675820000 or equivalent
Process EPS 8 Pins x 1	Molex 39-01-2080 or equivalent
PCIE x 2	

#### **Standard Output Cable Length:**

500 mm / 19.68 Inches

#### **PCB specific:**

- ▶ Layers: 4
- ▶ Copper: 3 Oz
- ▶ Thickness: 1.6 mm
- ▶ Material: FR4
- ▶ PCB material origin: Taiwan

#### **Power Chassis Dimension:**

225(L) x 150(W) x 86(H) mm / 8.86(L) x 5.9(W) x 3.39(H) Inches

#### **Rackmount Chassis solution:**

4U IPC Chassis 510mm Model No. GHI419ATX

**Screw hole:**

Front panel with 4 screw holes  
Rear panel bracket with 2 screw holes

**Net Weight:**

4.8 kg / 10.85 lbs

**Gross Weight:**

6 kg / 13.22 lbs

**Packing Detail:**

2 pcs  
12 kg / 26.45 lbs

**Measurement of Carton:**

0.045 m<sup>3</sup> / 1.59 Cuft

**Note:**

Power Supply is not able to be used in stand alone application  
Use Power Supply in Power Chassis Assembly only